

**Carrier Indentification in 900 Mhz Band in Delhi****Service Area**

<b>Block No</b>	<b>Uplink</b>		<b>Downlink</b>	
	<b>Start Carrier</b>	<b>Stop Carrier</b>	<b>Start carrier</b>	<b>Stop Carrier</b>
1	890.2	891.0	935.2	936.0
2	891.2	892.0	936.2	937.0
3	892.2	893.0	937.2	938.0
4	893.2	894.0	938.2	939.0
5	894.2	895.0	939.2	940.0
6	895.2	896.0	940.2	941.0
7	896.2	897.0	941.2	942.0
8	897.2	898.0	942.2	943.0
9	898.2	899.0	943.2	944.0
10	899.2	900.0	944.2	945.0
11	900.2	901.0	945.2	946.0
12	901.2	902.0	946.2	947.0
13	902.2	903.0	947.2	948.0
14	903.2	904.0	948.2	949.0
15	904.2	905.0	949.2	950.0
16	905.2	906.0	950.2	951.0

**Carrier Indentification in 900 MHz band in Mumbai****Service Area**

<b>Block No</b>	<b>Uplink</b>		<b>Downlink</b>	
	<b>Start</b>	<b>Stop</b>	<b>Start</b>	<b>Stop</b>
1	890.2	891.0	935.2	936.0
2	891.2	892.0	936.2	937.0
3	892.2	893.0	937.2	938.0
4	893.2	894.0	938.2	939.0
5	894.2	895.0	939.2	940.0
6	895.2	896.0	940.2	941.0
7	896.2	897.0	941.2	942.0
8	897.2	898.0	942.2	943.0
9	898.2	899.0	943.2	944.0
10	899.2	900.0	944.2	945.0
11	906.8	907.6	951.8	952.6
12	910.0	910.8	955.0	955.8
13	911.0	911.8	956.0	956.8
14	912.0	912.8	957.0	957.8
15	913.0	913.8	958.0	958.8
16	914.0	914.8	959.0	959.8

**Carrier Identification in 900 MHz band in Kolkata  
Service Area**

Block No	Uplink		Downlink	
	Start	Stop	Start	Stop
1	890.2	891.0	935.2	936.0
2	891.2	892.0	936.2	937.0
3	892.2	893.0	937.2	938.0
4	893.2	894.0	938.2	939.0
5	894.2	895.0	939.2	940.0
6	895.2	896.0	940.2	941.0
7	896.2	897.0	941.2	942.0
8	897.2	898.0	942.2	943.0
9	898.2	899.0	943.2	944.0
10	899.2	900.0	944.2	945.0
11	900.2	901.0	945.2	946.0
12	901.2	902.0	946.2	947.0
13	909.6	910.4	954.6	955.4
14	910.6	911.4	955.6	956.4

Each carrier is associated with 200 KHz bandwidth (100 KHz on both Side)

i.e. Carrier 890.2 MHz is 890.1 to 890.3 MHz

One block of 1 MHz is associated with 100 KHz on both side

Block 1: 890.1 MHz (Start) to 891.1 MHz (stop)